

*The **Oticon ConnectLine phone adapter** is an interface between a conventional landline phone installation and the Oticon Streamer Pro or the Oticon ConnectClip*, in effect turning a pair of Oticon hearing instruments into a wireless headset.*

As part of the ConnectLine system, the phone adapter works seamlessly and simultaneously with other ConnectLine solutions such as mobile phones, TV and the ConnectLine Microphone.

A fully integrated system

With ConnectLine the user is in control of the system, not the other way around. Advanced features such as AutoPriority and AutoConnect ensure that the user can hear and answer a phone call while watching TV.

Landline home phone

Phone adapter 2.0 is installed in parallel to an existing landline home phone installation.

Once a user is in range of the phone adapter, the Streamer Pro or ConnectClip is automatically connected and ready to receive calls (AutoConnect).

The call can easily be answered, with a single touch of a button on the Streamer Pro, at a distance of up to 30 meters from the phone adapter. From the ConnectClip, the call is answered by clicking the multi-button shortly.

AutoPriority

If a user is listening to the TV using the ConnectLine TV solution (or other audio sources), the AutoPriority feature ensures that an incoming call is notified.

AutoResume

Once the call is ended the Streamer Pro or ConnectClip automatically resumes to its previous state. E.g. back to the sound from the TV.

For more information please refer to:
www.oticon.com/phone



* Both Oticon Streamer Pro and ConnectClip can be paired with the Phone Adapter, but they will not work simultaneously. It is therefore recommended only to pair one at a time.

Included

- RJ11 - RJ11 cable for connection to landline home phone
- Power supply
- Instructions for use



Technical data

Product and Model name	ConnectLine Phone Adapter 2.0, Model BS-H200
Compatibility	Streamer Pro 1.4 and later, and ConnectClip 1.1 and later
Dimensions	124 x 80 x 21 mm; weight 100 g.
ConnectLine system features	AutoConnect: Will automatically connect to the Streamer Pro or ConnectClip when in range. AutoPriority: Incoming calls will be prioritised over e.g. TV sound. Proximity pairing: The phone adapter will automatically pair to the Streamer Pro or ConnectClip if the Streamer Pro or ConnectClip is in pairing mode.
Range	Up to 30 meters with Streamer Pro or ConnectClip (free line of sight)
Connections	Phone line in/out for interface to (analogue) landline home phone (PSTN) (RJ11/RJ11) ConnectLine in/out for direct interface to e.g. computer1
Power consumption	Max. 190 mA (using the included power supply)
Headset in	Max 6dBmV(RMS), 10 K Ω
Headset out	-15 – -10dBmV(RMS), 10 -100 Ω
Audio Bandwidth	License free 2,4 GHz (ISM band)
AutoConnect (range)	Yes (30 meters)
Audio Quality	Mono / 8 kHz sample frq
Frequency	80 Hz - 3.5 kHz (wireless)
Operating temperature	10 - 40 °C
Storage temperature	-20 - 70 °C
Emissions	Max. 39 dB μ V/m @ 3 meters. In compliance with all relevant standards

References:

1. A Computer interface cable is included with Streamer Pro and ConnectClip. Also available as an accessory.